

# Manual

## **Package Contents**

- 1 x Rockerz 660
- 1 x USB Type C charging cable
- 1 x AUX Cable
- 1 x Manual
- 1 x Warranty Card
- 1 x Catalogue



## To Pair with Bluetooth

- (1) When switched off, press and hold the MFB ("multifunction button) for 3 seconds to switch the headphone on. It will automatically enter pairing mode with a prompt, the blue and red LEDs flash alternatively to
- of available devices.
  (3) Choose 'Rockerz 660' from the list and if asked enter the pairing password '0000' to establish Bluetooth connectivity.
- (4) Once successfully connected, the blue LED flashes once every five seconds to indicate the same
- Note: The headphone automatically turns off if there is no pairing established in 5 minutes.

#### Functions

indicate the same.
(2) Power off: In any mode, press and hold the MFB for 5 seconds. A voice prompt will confirm the same. The red LEDs will flash for 1 second before the device turns off.
(3) Play/Pause Single tap the MFB to play/pause music

play a song or remove them to pause a song. This headphone is equipped with In-ear Detection feature that detects whenever the user puts on the headphone for listening and vice versa.

- volume. A beep will indicate maximum volume. (5) Volume down: Tap the volume "-" button in steps to decrease the volume. A beep will indicate minimum volume. (6) Answer/End call: Tap the MFB once when answering or ending a call to complete the action

- 2 seconds.

  (10) Reset Device (Clear Paired List): Press and hold the "+" and "-"buttons simultaneously for 5 seconds to clear the previous list of connected devices. The red and blue LEDs will flash 3 times to indicate the same.

  (11) Dual Pairing. To connect Rockerz 660 to two devices simultaneously, firstly connect the headphone to one of the devices. Then, switch both the headphone and the device off. Thereafter, connect the headphone to the second device, and again switch the first device on. The headphone will get connected to both devices. If not, connect the first device manually once again to activate dual pairing.

  (12) Voice Assistant. Long press the MFB for 2 seconds to wake up smart voice assistant.
- voice assistant (13) Redial: Triple tap the MFB for redialing the last contacted number (14) EQ Modes: You can switch between Signature Sound mode (Bass Mode) and Balanced Mode by short pressing the EQ button.

Signature Sound Mode is boAt's default bass mode, while Balanced Mode is more suitable for podcasts, news and voice based media.

### Charging

Use a USB Type C charging cable to charge the headphone through either a laptop or an adaptor.

(1) Low Battery: When the remaining talk time is less than 10 minutes, there is a 'low battery' prompt and red LED flashes quickly to indicate

(2) Charging: Solid red LED indicates that the headphone is being charged (please note that the headphone cannot be turned on while charging).

(3) Fully charged: Solid blue LED indicates the same.

## Specifications

Bluetooth Version	V5.0
Operating Range:	10m
Frequency:	20Hz-20000Hz
Driver Size:	40mm*2 Drivers
Battery:	1000mAh
Talk time:	Up to 60 hours
Music time:	Up to 60 hours
Charging Time:	About 60 Min
Charging Technology:	ASAP Charge Technology
Charging Port:	Type C
AUX compatible:	Yes
Driver Impedance:	16Ω
Sensitivity:	102dB ±3dB
Dual Pairing:	Yes
In-ear Detection:	Yes

## **Safety Precautions**

- battery by yourself, as this can lead to a fire or electrical breakdown. Any maintenance or servicing of the headphones should be done only through a qualified service provider/manufacturer.

  •Please clean the headphones with the utmost of care with only a damp
- liquid. In addition, ensure that the headphones are kept away from extremely hot or cold substances.

  Any damage to the headphones that is NOT a manufacturing issue will make the product's warranty null and void.

	THE PERSON
1) Charger/Brick/Adapter	5V 2A
	: Standard Cable (35 strands ico. 10mm diameter/ strand



Front

Back